

ETSI TS 102 622 V13.0.0 (2016-10)



TECHNICAL SPECIFICATION

**Smart Cards;
UICC - Contactless Front-end (CLF) Interface;
Host Controller Interface (HCI)
(Release 13)**

Reference

RTS/SCP-THClvd00

Keywords

smart card

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:
<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at
<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:
<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2016.
All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.
3GPP™ and **LTE™** are Trade Marks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.
GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Contents

Intellectual Property Rights	7
Foreword.....	7
Modal verbs terminology.....	7
1 Scope	8
2 References	8
2.1 Normative references	8
2.2 Informative references.....	9
3 Definitions, symbols and abbreviations	9
3.1 Definitions.....	9
3.2 Symbols.....	9
3.3 Abbreviations	10
3.4 Void.....	10
3A Coding conventions.....	10
4 HCI architecture	11
4.1 Overview	11
4.2 Hosts.....	11
4.3 Gates.....	12
4.4 Pipes	13
4.5 Registries.....	14
5 HCP.....	15
5.1 HCP packets	15
5.2 HCP message structure.....	15
5.3 Message fragmentation.....	16
6 Instructions	17
6.0 Foreword	17
6.1 Commands.....	17
6.1.1 Overview	17
6.1.2 Generic commands	18
6.1.2.1 ANY_SET_PARAMETER.....	18
6.1.2.2 ANY_GET_PARAMETER	18
6.1.2.3 ANY_OPEN_PIPE	18
6.1.2.4 ANY_CLOSE_PIPE	19
6.1.3 Administration commands.....	19
6.1.3.1 ADM_CREATE_PIPE.....	19
6.1.3.2 ADM_NOTIFY_PIPE_CREATED	19
6.1.3.3 ADM_DELETE_PIPE.....	20
6.1.3.4 ADM_NOTIFY_PIPE_DELETED.....	20
6.1.3.5 ADM_CLEAR_ALL_PIPE	20
6.1.3.6 ADM_NOTIFY_ALL_PIPE_CLEARED.....	21
6.2 Responses	21
6.3 Events	22
6.3.1 Generic events	22
6.3.2 EVT_HOT_PLUG parameters.....	23
6.3.3 EVT_TERMINAL_HOST_REQUEST parameters	23
6.3.4 EVT_TERMINAL_HOST_INFORMATION parameters	23
7 GATES	24
7.0 Generic gate events and command support	24
7.1 Management gates.....	25
7.1.1 Administration gates	25
7.1.1.1 Host controller administration gate	25
7.1.1.2 Host administration gate	28
7.1.2 Link management gate.....	28

7.1.2.1	Host controller link management gate.....	28
7.1.2.2	Host link management gate.....	28
7.1.3	Identity management gate.....	29
7.1.4	Loop back gate.....	29
7.2	Generic gates.....	29
8	HCI procedures.....	30
8.1	Pipe management.....	30
8.1.1	Pipe creation.....	30
8.1.2	Pipe deletion.....	32
8.1.3	Clear all Pipes.....	33
8.2	Registry access.....	33
8.3	Host and Gate discovery.....	34
8.4	Session initialization.....	35
8.5	Loop back testing.....	36
9	Contactless card emulation.....	37
9.1	Overview.....	37
9.2	Void.....	38
9.3	Gates.....	38
9.3.1	Void.....	38
9.3.2	Identity management gate.....	38
9.3.3	Card RF gates.....	39
9.3.3.1	Overview.....	39
9.3.3.2	Commands.....	39
9.3.3.3	Events.....	39
9.3.3.3.0	Supported events.....	39
9.3.3.3.1	EVT_SEND_DATA.....	39
9.3.3.4	Registry.....	39
9.3.3.4.0	Registries persistence.....	39
9.3.3.4.1	RF technology type A.....	39
9.3.3.4.2	RF technology type B.....	41
9.3.3.4.3	RF technology type B'.....	42
9.3.3.4.4	RF technology Type F (ISO/IEC 18092 212 kbps/424 kbps card emulation only).....	43
9.3.4	Card application gates.....	43
9.3.4.1	Overview.....	43
9.3.4.2	Commands.....	44
9.3.4.3	Events.....	44
9.3.4.3.0	Supported events.....	44
9.3.4.3.1	EVT_FIELD_ON.....	44
9.3.4.3.2	EVT_CARD_DEACTIVATED.....	44
9.3.4.3.3	EVT_CARD_ACTIVATED.....	44
9.3.4.3.4	EVT_FIELD_OFF.....	44
9.3.4.3.5	EVT_SEND_DATA.....	44
9.3.4.4	Registry.....	45
9.4	Procedures.....	45
9.4.0	Overview and basic rule.....	45
9.4.1	Use of contactless card application.....	45
9.4.2	Non ISO/IEC 14443-4 type A applications.....	46
9.4.3	Type B' RF technology.....	46
9.4.4	Type F RF technology.....	47
9.4.5	Update RF technology settings.....	48
9.4.6	Identity check.....	48
10	Contactless reader.....	48
10.1	Overview.....	48
10.2	Reader RF gates.....	49
10.2.1	Overview.....	49
10.2.2	Command.....	50
10.2.2.1	WR_XCHG_DATA.....	50
10.2.3	Registries.....	51
10.2.3.1	Type A reader RF gate.....	51
10.2.3.2	Type B reader RF gate.....	52

10.2.4	Events	53
10.2.4.0	Supported events	53
10.2.4.1	EVT_READER_REQUESTED	53
10.2.4.2	EVT_END_OPERATION	53
10.2.5	Responses	53
10.3	Reader application gates	53
10.3.1	Overview	53
10.3.2	Command	53
10.3.3	Registry	54
10.3.4	Events	54
10.3.4.0	Supported events	54
10.3.4.1	EVT_TARGET_DISCOVERED	54
10.3.4.2	EVT_READER_STATUS	54
10.4	Reader mode procedures	55
10.4.1	Use of contactless reader application	55
10.4.2	Contactless reader not available	56
10.4.3	Error management	57
11	Connectivity	57
11.1	Overview	57
11.2	Connectivity gate	58
11.2.0	Overview	58
11.2.1	Commands	58
11.2.1.1	PRO_HOST_REQUEST	58
11.2.2	Events	58
11.2.2.0	Supported events	58
11.2.2.1	EVT_CONNECTIVITY	58
11.2.2.2	Void	59
11.2.2.3	EVT_OPERATION_ENDED	59
11.2.2.4	EVT_TRANSACTION	59
11.2.2.5	EVT_MH_NOTIFICATION	59
11.2.3	Registry	59
11.3	Connectivity application gate	60
11.3.0	Overview	60
11.3.1	Commands	60
11.3.2	Events	60
11.3.2.0	Supported events	60
11.3.2.1	EVT_STANDBY	60
11.3.2.2	EVT_HOST_NOTIFICATION	60
11.3.3	Registry	61
11.4	Connectivity gate procedures	61
11.4.1	Use of connectivity gate	61
12	APDU Transport	61
12.1	Overview	61
12.2	APDU gate	62
12.2.0	Description	62
12.2.1	Commands	62
12.2.2	Events	62
12.2.2.0	Supported events	62
12.2.2.1	EVT_C-APDU	62
12.2.2.2	EVT_ABORT	63
12.2.2.3	EVT_END_OF_APDU_TRANSACTION	63
12.2.3	Registry	63
12.3	APDU application gate	63
12.3.0	Description	63
12.3.1	Commands	63
12.3.2	Events	64
12.3.2.0	Supported events	64
12.3.2.1	EVT_R-APDU	64
12.3.2.2	EVT_WTX	64
12.3.2.3	EVT_ATR	64

12.3.3	Registry	65
12.4	State diagram for the APDU gate	65
13	Managing Host Interface	66
13.1	Overview	66
13.2	Platform Management gate	66
13.2.1	Description	66
13.2.2	Commands	66
13.2.3	Events	67
13.2.3.1	Supported events	67
13.2.3.2	EVT_MH_NOTIFICATION	67
13.2.4	Registry	67
13.3	Platform Management application gate	67
13.3.1	Description	67
13.3.2	Commands	67
13.3.3	Events	67
13.3.3.1	Supported events	67
13.3.3.2	EVT_HOST_NOTIFICATION	68
13.3.4	Registry	68
13.3.4.1	Description	68
13.3.4.2	CLF capabilities	68
13.3.4.3	Routing registry	69
13.3.4.4	RF parameters registry	69
13.4	Routing mechanism description	70
13.5	Procedures	70
Annex A (normative):	State diagram for contactless reader mode	72
Annex B (informative):	Change history	73
History		75

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI Technical Committee Smart Card Platform (SCP).

The contents of the present document are subject to continuing work within TC SCP and may change following formal TC SCP approval. If TC SCP modifies the contents of the present document, it will then be republished by ETSI with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 0 early working draft;
 - 1 presented to TC SCP for information;
 - 2 presented to TC SCP for approval;
 - 3 or greater indicates TC SCP approved document under change control.
- Y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

1 Scope

The present document specifies a logical interface that enables contactless applications hosted on the UICC. The present document covers the configuration where the one host is embedded in the UICC which is connected to the host controller embedded in the CLF.

The interface is specified in two parts:

- the HCI core as described in the first part of the present document (clauses 4 to 8), specifies an application independent logical interface; and
- the contactless platform as described in the second part of the present document (clauses 9 to 11) specifies an implementation of the HCI core for contactless applications using the UICC and the CLF.

Lower layer protocols that support the HCI like the SWP specified in ETSI TS 102 613 [2] are out of the scope of the present document.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

- In the case of a reference to a TC SCP document, a non specific reference implicitly refers to the latest version of that document in the same Release as the present document.

Referenced documents which are not found to be publicly available in the expected location might be found at <https://docbox.etsi.org/Reference/>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are necessary for the application of the present document.

- [1] Void.
- [2] ETSI TS 102 613: "Smart Cards; UICC - Contactless Front-end (CLF) Interface; Part 1: Physical and data link layer characteristics".
- [3] ETSI TS 102 223: "Smart Cards; Card Application Toolkit (CAT)".
- [4] ISO/IEC 18092: "Information technology - Telecommunications and information exchange between systems - Near Field Communication - Interface and Protocol (NFCIP-1)".
- [5] ISO/IEC 14443-2: "Identification cards - Contactless integrated circuit(s) cards - Proximity cards - Part 2: Radio frequency power and signal interface".
- [6] ISO/IEC 14443-3: "Identification cards - Contactless integrated circuit(s) cards - Proximity cards - Part 3: Initialization and anticollision".
- [7] ISO/IEC 14443-4: "Identification cards - Contactless integrated circuit cards - Proximity cards - Part 4: Transmission protocol".
- [8] ISO/IEC 7816-4: "Identification cards - Integrated circuit cards - Part 4: Organization, security and commands for interchange".
- [9] ETSI TS 101 220: "Smart Cards; ETSI numbering system for telecommunication application providers".