

Information technology equipment — Safety —

Part 1: General requirements

The European Standard EN 60950-1:2006 has the status of a
British Standard

ICS 35.020; 35.260

National foreword

This British Standard is the official English language version of EN 60950-1:2006. It was derived by CENELEC from IEC 60950-1:2005. It supersedes BS EN 60950-1:2002 which will be withdrawn on 1 December 2010.

The CENELEC common modifications have been implemented at the appropriate places in the text and are indicated by tags (e.g. **Ⓒ** **Ⓒ**).

The UK participation in its preparation was entrusted to Technical Committee EPL/108, Safety of electronic equipment within the field of audio/video, information technology and communication technology, which has the responsibility to:

- aid enquirers to understand the text;
- present to the responsible international/European committee any enquiries on the interpretation, or proposals for change, and keep UK interests informed;
- monitor related international and European developments and promulgate them in the UK.

A list of organizations represented on this committee can be obtained on request to its secretary.

Cross-references

The British Standards which implement international or European publications referred to in this document may be found in the *BSI Catalogue* under the section entitled “International Standards Correspondence Index”, or by using the “Search” facility of the *BSI Electronic Catalogue* or of British Standards Online.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

Compliance with a British Standard does not of itself confer immunity from legal obligations.

Summary of pages

This document comprises a front cover, an inside front cover, the EN title page, pages 2 to 312, an inside back cover and a back cover.

The BSI copyright notice displayed in this document indicates when the document was last issued.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 May 2006

© BSI 2006

Amendments issued since publication

Amd. No.	Date	Comments
16481 Corrigendum No.1	June 2006	Correction to formatting errors at printing stage
16565 Corrigendum No. 2	August 2006	Correction to numbering of subclause 2.7

EUROPEAN STANDARD

EN 60950-1

NORME EUROPÉENNE

EUROPÄISCHE NORM

April 2006

ICS 35.020; 35.260

Supersedes EN 60950-1:2001 + A11:2004

English version

**Information technology equipment -
Safety**

Part 1: General requirements
(IEC 60950-1:2005, modified)

Matériel de traitement de l'information -
Sécurité

Partie 1: Exigences générales
(CEI 60950-1:2005, modifiée)

Einrichtungen der Informationstechnik -
Sicherheit

Teil 1: Allgemeine Anforderungen
(IEC 60950-1:2005, modifiziert)

This European Standard was approved by CENELEC on 2005-12-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the Central Secretariat or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the Central Secretariat has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Central Secretariat: rue de Stassart 35, B - 1050 Brussels

Foreword

The text of document 108/135A/FDIS, future edition 2 of IEC 60950-1, prepared by IEC TC 108, Safety of electronic equipment within the field of audio/video, information technology and communication technology, was submitted to the IEC-CENELEC parallel.

This text, together with a draft amendment, prepared by the Technical Committee CENELEC TC 108, Safety of electronic equipment within the fields of audio/video, information technology and communication technology, and submitted to the formal vote, was approved by CENELEC as EN 60950-1 on 2005-12-01.

This European Standard supersedes EN 60950-1:2001 + corrigendum April 2004 + A11:2004.

EN 60950-1 includes the basic requirements for the safety of information technology equipment.

Additional parts of EN 60950-1 will cover specific safety requirements for information technology equipment having limited applications or having special features as follows:

Part 21: Remote power feeding;

Part 22: Equipment installed outdoors;

Part 23: Large data storage equipment.

Except for notes, all text within a normative figure, or in a box under a normative table, is also normative. Text with a superscript reference is linked to a particular item in the table. Other text in a box under a table applies to the whole table.

Informative annexes and text beginning with the word "NOTE" are not normative. They are provided only to give additional information.

In this standard, the following print types are used:

- Requirements proper and normative annexes: roman type.
- *Compliance statements and test specifications: italic type.*
- Notes in the text and in tables: smaller roman type.
- Terms that are defined in 1.2: SMALL CAPITALS.

The following dates were fixed:

- latest date by which the EN has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2006-12-01
- latest date by which the national standards conflicting with the EN have to be withdrawn (dow) 2010-12-01

Clauses, subclauses, notes, tables and figures which are additional to those in IEC 60950-1 are prefixed "Z".

Annexes ZA, ZB and ZC have been added by CENELEC.

Endorsement notice

The text of the International Standard IEC 60950-1:2005 was approved by CENELEC as a European Standard with agreed common modifications.

CONTENTS

INTRODUCTION.....	9
0 Principles of safety	9
0.1 General principles of safety	9
0.2 Hazards	10
0.3 Materials and components	14
1 General	15
1.1 Scope.....	15
1.2 Definitions	17
1.3 General requirements	33
1.4 General conditions for tests	34
1.5 Components	39
1.6 Power interface	46
1.7 Markings and instructions	46
2 Protection from hazards.....	54
2.1 Protection from electric shock and energy hazards	54
2.2 SELV circuits.....	63
2.3 TNV circuits.....	65
2.4 Limited current circuits.....	70
2.5 Limited power sources	71
2.6 Provisions for earthing and bonding	73
2.7 Overcurrent and earth fault protection in primary circuits	81
2.8 Safety interlocks	84
2.9 Electrical insulation	87
2.10 Clearances, creepage distances and distances through insulation	92
3 Wiring, connections and supply.....	120
3.1 General	120
3.2 Connection to a mains supply	123
3.3 Wiring terminals for connection of external conductors	130
3.4 Disconnection from the mains supply	133
3.5 Interconnection of equipment	136
4 Physical requirements	137
4.1 Stability.....	137
4.2 Mechanical strength.....	138
4.3 Design and construction	142
4.4 Protection against hazardous moving parts	151
4.5 Thermal requirements	152
4.6 Openings in enclosures	156
4.7 Resistance to fire.....	163
5 Electrical requirements and simulated abnormal conditions	172
5.1 Touch current and protective conductor current.....	172
5.2 Electric strength	181
5.3 Abnormal operating and fault conditions.....	185

6	Connection to telecommunication networks	189
6.1	Protection of telecommunication network service persons, and users of other equipment connected to the network, from hazards in the equipment.....	190
6.2	Protection of equipment users from overvoltages on telecommunication networks	192
6.3	Protection of the telecommunication wiring system from overheating	194
7	Connection to cable distribution systems.....	195
7.1	General.....	195
7.2	Protection of cable distribution system service persons, and users of other equipment connected to the system, from hazardous voltages in the equipment.....	195
7.3	Protection of equipment users from overvoltages on the cable distribution system.....	195
7.4	Insulation between primary circuits and cable distribution systems.....	196
Annex A (normative)	Tests for resistance to heat and fire	198
Annex B (normative)	Motor tests under abnormal conditions	201
Annex C (normative)	Transformers.....	207
Annex D (normative)	Measuring instruments for touch current tests	211
Annex E (normative)	Temperature rise of a winding.....	213
Annex F (normative)	Measurement of clearances and creepage distances	214
Annex G (normative)	Alternative method for determining minimum clearances	222
Annex H (normative)	Ionizing radiation	230
Annex J (normative)	Table of electrochemical potentials (see 2.6.5.6).....	231
Annex K (normative)	Thermal controls.....	232
Annex L (normative)	Normal load conditions for some types of electrical business equipment	234
Annex M (normative)	Criteria for telephone ringing signals.....	236
Annex N (normative)	Impulse test generators	241
Annex P (normative)	Normative references.....	243
Annex Q (normative)	Voltage dependent resistors (VDRs)	247
Annex R (informative)	Examples of requirements for quality control programmes	248
Annex S (informative)	Procedure for impulse testing.....	251
Annex T (informative)	Guidance on protection against ingress of water	253
Annex U (normative)	Insulated winding wires for use without interleaved insulation.....	255
Annex V (normative)	AC power distribution systems	258
Annex W (informative)	Summation of touch currents.....	265
Annex X (informative)	Maximum heating effect in transformer tests.....	268
Annex Y (normative)	Ultraviolet light conditioning test.....	270
Annex Z (informative)	Overvoltage categories (see 2.10.3.2 and Clause G.2).....	271
Annex AA (normative)	Mandrel test (see 2.10.5.8).....	272
Annex BB (informative)	Changes in the second edition	275
Annex ZA (normative)	Normative references to international publications with their corresponding European publications	303
Annex ZB (normative)	Special national conditions	307
Annex ZC (informative)	A-deviations	311

Bibliography	278
Index	281
Figure 2A – Test finger	56
Figure 2B – Test pin	57
Figure 2C – Test probe	57
Figure 2D - Accessibility of internal conductive parts	58
Figure 2E – Voltages in SELV circuits under single fault conditions.....	64
Figure 2F – Maximum voltages permitted after a single fault.....	66
Figure 2G – Test generator	70
Figure 2H – Examples of application of insulation	91
Figure 2J – Thermal ageing time	117
Figure 2K – Abrasion resistance test for coating layers.....	118
Figure 4A – Impact test using a steel ball	140
Figure 4B – Examples of cross-sections of designs of openings preventing vertical access.....	157
Figure 4C – Examples of louvre design	157
Figure 4D – Enclosure openings.....	158
Figure 4E – Typical bottom of a fire enclosure for partially enclosed component or assembly.....	159
Figure 4F – Baffle plate construction	160
Figure 5A – Test circuit for touch current of single-phase equipment on a star TN or TT power supply system	174
Figure 5B – Test circuit for touch current of three-phase equipment on a star TN or TT power supply system	174
Figure 6A – Test for separation between a telecommunication network and earth.....	191
Figure 6B – Application points of test voltage	192
Figure B.1 – Determination of arithmetic average temperature	202
Figure C.1 – Determination of arithmetic average temperature	208
Figure D.1 – Measuring instrument.....	211
Figure D.2 – Alternative measuring instrument	212
Figure F.1 – Narrow groove	215
Figure F.2 – Wide groove.....	215
Figure F.3 – V-shaped groove	215
Figure F.4 – Rib.....	215
Figure F.5 – Uncemented joint with narrow groove	216
Figure F.6 – Uncemented joint with wide groove	216
Figure F.7 – Uncemented joint with narrow and wide grooves	216
Figure F.8 – Narrow recess.....	217
Figure F.9 – Wide recess	217
Figure F.10 – Coating around terminals.....	218

Figure F.11 – Coating over printed wiring	218
Figure F.12 – Measurements through openings in enclosures	219
Figure F.13 – Intervening, unconnected conductive part	219
Figure F.14 – Solid insulating material.....	220
Figure F.15 – Thin sheet insulating material	220
Figure F.16 – Cemented joints in multi-layer printed board.....	220
Figure F.17 – Component filled with insulating compound	221
Figure F.18 – Partitioned bobbin	221
Figure M.1 – Definition of ringing period and cadence cycle	237
Figure M.2 – I_{TS1} limit curve for cadenced ringing signal	238
Figure M.3 – Peak and peak-to-peak currents.....	238
Figure M.4 – Ringing voltage trip criteria	240
Figure N.1 – ITU-T impulse test generator circuit.....	241
Figure N.2 – IEC 60065 impulse test generator circuit	242
Figure S.1 – Waveform on insulation without surge suppressors and no breakdown	251
Figure S.2 – Waveforms on insulation during breakdown without surge suppressors	252
Figure S.3 – Waveforms on insulation with surge suppressors in operation	252
Figure S.4 – Waveform on short-circuited surge suppressor and insulation	252
Figure V.1 – Examples of TN-S power distribution systems.....	260
Figure V.2 – Example of TN-C-S power distribution system.....	261
Figure V.3 – Example of TN-C power distribution system.....	261
Figure V.4 – Example of single-phase, three-wire TN-C power distribution system	262
Figure V.5 – Example of three line and neutral TT power distribution system.....	262
Figure V.6 – Example of three line TT power distribution system.....	263
Figure V.7 – Example of three line (and neutral) IT power distribution system	263
Figure V.8 – Example of three line IT power distribution system.....	264
Figure W.1 – Touch current from a floating circuit.....	265
Figure W.2 – Touch current from an earthed circuit	266
Figure W.3 – Summation of touch currents in a PABX.....	266
Figure AA.1 – Mandrel	272
Figure AA.2 – Initial position of mandrel	273
Figure AA.3 – Final position of mandrel	273
Table 1A – Voltage ranges of SELV and TNV circuits	25
Table 1B – Equivalence of flammability classes	29
Table 1C – Capacitor ratings according to IEC 60384-14	41
Table 1D – Informative examples of application of capacitors	42
Table 2A – Distance through insulation of internal wiring	59
Table 2B – Limits for power sources without an overcurrent protective device	72
Table 2C – Limits for power sources with an overcurrent protective device.....	72

Table 2D – Minimum size of protective bonding conductors	76
Table 2E – Test duration, a.c. mains supplies.....	77
Table 2F – Informative examples of protective devices in single-phase equipment or subassemblies.....	83
Table 2G – Informative examples of protective devices in three-phase equipment	83
Table 2H – Examples of application of insulation	89
Table 2J – AC mains transient voltages.....	97
Table 2K – Minimum clearances for insulation in primary circuits and between primary and secondary circuits	98
Table 2L – Additional clearances in primary circuits.....	99
Table 2M – Minimum clearances in secondary circuits	100
Table 2N – Minimum creepage distances	105
Table 2P – Tests for insulation in non-separable layers	109
Table 2Q – Minimum separation distances for coated printed boards	114
Table 2R – Insulation in printed boards	115
Table 3A – Sizes of cables and conduits for equipment having a rated current not exceeding 16 A.....	125
Table 3B – Sizes of conductors	127
Table 3C – Physical tests on power supply cords	129
Table 3D – Range of conductor sizes to be accepted by terminals	131
Table 3E – Sizes of terminals for mains supply conductors and protective earthing conductors	132
Table 4A – Minimum property retention limits after UV exposure.....	148
Table 4B – Temperature limits, materials and components.....	154
Table 4C – Touch temperature limits	155
Table 4D – Size and spacing of openings in metal bottoms of fire enclosures.....	161
Table 4E – Summary of material flammability requirements	171
Table 5A – Maximum current.....	176
Table 5B – Test voltages for electric strength tests based on peak working voltages Part 1..	183
Table 5B – Test voltages for electric strength tests based on peak working voltages Part 2..	184
Table 5C – Test voltages for electric strength tests based on required withstand voltages .	185
Table 5D – Temperature limits for overload conditions.....	189
Table B.1 – Temperature limits for motor windings (except for running overload test)	202
Table B.2 – Permitted temperature limits for running overload tests	203
Table C.1 – Temperature limits for transformer windings.....	208
Table F.1 – Value of X	214
Table G.1 – AC mains transient voltages	223

Table G.2 – Minimum clearances up to 2 000 m above sea level.....	228
Table J.1 – Electrochemical potentials (V).....	231
Table N.1 – Component values for Figures N.1 and N.2.....	242
Table R.1 – Rules for sampling and inspection – coated printed boards	249
Table R.2 – Rules for sampling and inspection – reduced clearances.....	250
Table T.1 – Extract from IEC 60529	254
Table U.1 – Mandrel diameter	256
Table U.2 – Oven temperature	256
Table X.1 – Test steps	269
Table Z.1 – Overvoltage categories.....	271

INTRODUCTION

0 Principles of safety

The following principles have been adopted by technical committee 108 in the development of this standard.

These principles do not cover performance or functional characteristics of equipment.

Words printed in SMALL CAPITALS are terms that are defined in 1.2 of this standard.

0.1 General principles of safety

It is essential that designers understand the underlying principles of safety requirements in order that they can engineer safe equipment.

These principles are not an alternative to the detailed requirements of this standard, but are intended to provide designers with an appreciation of the basis of these requirements. Where the equipment involves technologies and materials or methods of construction not specifically covered, the design of the equipment should provide a level of safety not less than those described in these principles of safety.

Designers shall take into account not only normal operating conditions of the equipment but also likely fault conditions, consequential faults, foreseeable misuse and external influences such as temperature, altitude, pollution, moisture, overvoltages on the MAINS SUPPLY and overvoltages on a TELECOMMUNICATION NETWORK or a CABLE DISTRIBUTION SYSTEM. Dimensioning of insulation spacings should take account of possible reductions by manufacturing tolerances, or where deformation could occur due to handling, shock and vibration likely to be encountered during manufacture, transport and normal use.

The following priorities should be observed in determining what design measures to adopt:

- where possible, specify design criteria that will eliminate, reduce or guard against hazards;
- where the above is not practicable because the functioning of the equipment would be impaired, specify the use of protective means independent of the equipment, such as personal protective equipment (which is not specified in this standard);
- where neither of the above measures is practicable, or in addition to those measures, specify the provision of markings and instructions regarding the residual risks.

There are two types of persons whose safety needs to be considered, USERS (or OPERATORS) and SERVICE PERSONS.

USER is the term applied to all persons other than SERVICE PERSONS. Requirements for protection should assume that USERS are not trained to identify hazards, but will not intentionally create a hazardous situation. Consequently, the requirements will provide protection for cleaners and casual visitors as well as the assigned USERS. In general, USERS should not have access to hazardous parts, and to this end, such parts should only be in SERVICE ACCESS AREAS or in equipment located in RESTRICTED ACCESS LOCATIONS.

When USERS are admitted to RESTRICTED ACCESS LOCATIONS they shall be suitably instructed.

SERVICE PERSONS are expected to use their training and skill to avoid possible injury to themselves and others due to obvious hazards that exist in SERVICE ACCESS AREAS of the equipment or on equipment located in RESTRICTED ACCESS LOCATIONS. However, SERVICE

PERSONS should be protected against unexpected hazards. This can be done by, for example, locating parts that need to be accessible for servicing away from electrical and mechanical hazards, providing shields to avoid accidental contact with hazardous parts, and providing labels or instructions to warn personnel about any residual risk.

Information about potential hazards can be marked on the equipment or provided with the equipment, depending on the likelihood and severity of injury, or made available for SERVICE PERSONS. In general, USERS shall not be exposed to hazards likely to cause injury, and information provided for USERS should primarily aim at avoiding misuse and situations likely to create hazards, such as connection to the wrong power source and replacement of fuses by incorrect types.

MOVABLE EQUIPMENT is considered to present a slightly increased risk of shock, due to possible extra strain on the supply cord leading to rupture of the earthing conductor. With HAND-HELD EQUIPMENT, this risk is increased; wear on the cord is more likely, and further hazards could arise if the units were dropped. TRANSPORTABLE EQUIPMENT introduces a further factor because it can be used and carried in any orientation; if a small metallic object enters an opening in the ENCLOSURE it can move around inside the equipment, possibly creating a hazard.

0.2 Hazards

Application of a safety standard is intended to reduce the risk of injury or damage due to the following:

- electric shock;
- energy related hazards;
- fire;
- heat related hazards;
- mechanical hazards;
- radiation;
- chemical hazards.

0.2.1 Electric shock

Electric shock is due to current passing through the human body. The resulting physiological effects depend on the value and duration of the current and the path it takes through the body. The value of the current depends on the applied voltage, the impedance of the source and the impedance of the body. The body impedance depends in turn on the area of contact, moisture in the area of contact and the applied voltage and frequency. Currents of approximately half a milliampere can cause a reaction in persons in good health and may cause injury indirectly due to involuntary reaction. Higher currents can have more direct effects, such as burn or muscle tetanization leading to inability to let go or to ventricular fibrillation.

Steady state voltages up to 42,4 V peak, or 60 V d.c., are not generally regarded as hazardous under dry conditions for an area of contact equivalent to a human hand. Bare parts that have to be touched or handled should be at earth potential or properly insulated.

Some equipment will be connected to telephone and other external networks. Some TELECOMMUNICATION NETWORKS operate with signals such as voice and ringing superimposed on a steady d.c. supply voltage; the total may exceed the values given above for steady-state voltages. It is common practice for the SERVICE PERSONS of telephone companies to handle parts of such circuits bare-handed. This has not caused serious injury, because of the use of cadenced ringing and because there are limited areas of contact with bare conductors normally handled by SERVICE PERSONS. However, the area of contact of a part accessible to the USER, and the likelihood of the part being touched, should be further limited (for example, by the shape and location of the part).

It is normal to provide two levels of protection for USERS to prevent electric shock. Therefore, the operation of equipment under normal conditions and after a single fault, including any consequential faults, should not create a shock hazard. However, provision of additional protective measures, such as protective earthing or SUPPLEMENTARY INSULATION, is not considered a substitute for, or a relief from, properly designed BASIC INSULATION.

Harm may result from:

Contact with bare parts normally at HAZARDOUS VOLTAGES.

Breakdown of insulation between parts normally at HAZARDOUS VOLTAGES and accessible conductive parts.

Examples of measures to reduce risks:

Prevent USER access to parts at HAZARDOUS VOLTAGES by fixed or locked covers, SAFETY INTERLOCKS, etc. Discharge accessible capacitors that are at HAZARDOUS VOLTAGES.

Provide BASIC INSULATION and connect the accessible conductive parts and circuits to earth so that exposure to the voltage which can develop is limited because overcurrent protection will disconnect the parts having low impedance faults within a specified time; or provide a metal screen connected to protective earth between the parts, or provide DOUBLE INSULATION or REINFORCED INSULATION between the parts, so that breakdown to the accessible part is not likely to occur.

Contact with circuits connected to TELECOMMUNICATION NETWORKS that exceed 42,4 V peak or 60 V d.c.

Limit the accessibility and area of contact of such circuits, and separate them from unearthed parts to which access is not limited.

Breakdown of USER-accessible insulation.

Insulation that is accessible to the USER should have adequate mechanical and electrical strength to reduce the likelihood of contact with HAZARDOUS VOLTAGES.

TOUCH CURRENT (leakage current) flowing from parts at HAZARDOUS VOLTAGES to accessible parts, or failure of a protective earthing connection. TOUCH CURRENT may include current due to EMC filter components connected between PRIMARY CIRCUITS and accessible parts.

Limit TOUCH CURRENT to a specified value, or provide a high integrity protective earthing connection.

0.2.2 Energy related hazards

Injury or fire may result from a short-circuit between adjacent poles of high current supplies or high capacitance circuits, causing:

- burns;
- arcing;
- ejection of molten metal.

Even circuits whose voltages are safe to touch may be hazardous in this respect.

Examples of measures to reduce risks include:

- separation;
- shielding;
- provision of SAFETY INTERLOCKS.

0.2.3 Fire

Risk of fire may result from excessive temperatures either under normal operating conditions or due to overload, component failure, insulation breakdown or loose connections. Fires originating within the equipment should not spread beyond the immediate vicinity of the source of the fire, nor cause damage to the surroundings of the equipment.

Examples of measures to reduce risks include:

- providing overcurrent protection;
- using constructional materials having appropriate flammability properties for their purpose;
- selection of parts, components and consumable materials to avoid high temperature which might cause ignition;
- limiting the quantity of combustible materials used;

- shielding or separating combustible materials from likely ignition sources;
- using ENCLOSURES or barriers to limit the spread of fire within the equipment;
- using suitable materials for ENCLOSURES so as to reduce the likelihood of fire spreading from the equipment.

0.2.4 Heat related hazards

Injury may result from high temperatures under normal operating conditions, causing:

- burns due to contact with hot accessible parts;
- degradation of insulation and of safety-critical components;
- ignition of flammable liquids.

Examples of measures to reduce risks include:

- taking steps to avoid high temperature of accessible parts;
- avoiding temperatures above the ignition point of liquids;
- provision of markings to warn USERS where access to hot parts is unavoidable.

0.2.5 Mechanical hazards

Injury may result from:

- sharp edges and corners;
- moving parts that have the potential to cause injury;
- equipment instability;
- flying particles from imploding cathode ray tubes and exploding high pressure lamps.

Examples of measures to reduce risks include:

- rounding of sharp edges and corners;
- guarding;
- provision of SAFETY INTERLOCKS;
- providing sufficient stability to free-standing equipment;
- selecting cathode ray tubes and high pressure lamps that are resistant to implosion and explosion respectively;
- provision of markings to warn USERS where access is unavoidable.

0.2.6 Radiation

Injury to USERS and to SERVICE PERSONS may result from some forms of radiation emitted by equipment. Examples are sonic (acoustic), radio frequency, infra-red, ultraviolet and ionizing radiation, and high intensity visible and coherent light (lasers).

Examples of measures to reduce risks include:

- limiting the energy level of potential radiation sources;
- screening radiation sources;
- provision of SAFETY INTERLOCKS;
- provision of markings to warn USERS where exposure to the radiation hazard is unavoidable.

0.2.7 Chemical hazards

Injury may result from contact with some chemicals or from inhalation of their vapours and fumes.

Examples of measures to reduce risks include:

- avoiding the use of constructional and consumable materials likely to cause injury by contact or inhalation during intended and normal conditions of use;
- avoiding conditions likely to cause leakage or vaporization;
- provision of markings to warn USERS about the hazards.

0.3 Materials and components

Materials and components used in the construction of equipment should be so selected and arranged that they can be expected to perform in a reliable manner for the anticipated life of the equipment without creating a hazard, and would not contribute significantly to the development of a serious fire hazard. Components should be selected so that they remain within their manufacturers' ratings under normal operating conditions, and do not create a hazard under fault conditions.

INFORMATION TECHNOLOGY EQUIPMENT – SAFETY –

Part 1: General requirements

1 General

1.1 Scope

1.1.1 Equipment covered by this standard

This standard is applicable to mains-powered or battery-powered information technology equipment, including electrical business equipment and associated equipment, with a RATED VOLTAGE not exceeding 600 V.

This standard is also applicable to such information technology equipment:

- designed for use as telecommunication terminal equipment and TELECOMMUNICATION NETWORK infrastructure equipment, regardless of the source of power;
- designed and intended to be connected directly to, or used as infrastructure equipment in, a CABLE DISTRIBUTION SYSTEM, regardless of the source of power;
- designed to use the AC MAINS SUPPLY as a communication transmission medium (see Clause 6, Note 4 and 7.1, Note 4).

This standard is also applicable to components and subassemblies intended for incorporation in information technology equipment. It is not expected that such components and subassemblies comply with every aspect of the standard, provided that the complete information technology equipment, incorporating such components and subassemblies, does comply.

NOTE 1 Examples of aspects with which uninstalled components and subassemblies may not comply include the marking of the power rating and access to hazardous parts.

NOTE 2 This standard may be applied to the electronic parts of equipment even if that equipment does not wholly fall within its Scope, such as large-scale air conditioning systems, fire detection systems and fire extinguishing systems. Different requirements may be necessary for some applications.

This standard specifies requirements intended to reduce risks of fire, electric shock or injury for the OPERATOR and layman who may come into contact with the equipment and, where specifically stated, for a SERVICE PERSON.

This standard is intended to reduce such risks with respect to installed equipment, whether it consists of a system of interconnected units or independent units, subject to installing, operating and maintaining the equipment in the manner prescribed by the manufacturer.

Examples of equipment that is in the scope of this standard are:

Generic product type	Specific example of generic type
banking equipment	monetary processing machines including automated teller (cash dispensing) machines (ATM)
data and text processing machines and associated equipment	data preparation equipment, data processing equipment, data storage equipment, personal computers, plotters, printers, scanners, text processing equipment, visual display units
data network equipment	bridges, data circuit terminating equipment, data terminal equipment, routers
electrical and electronic retail equipment	cash registers, point of sale terminals including associated electronic scales
electrical and electronic office machines	calculators, copying machines, dictation equipment, document shredding machines, duplicators, erasers, micrographic office equipment, motor-operated files, paper trimmers (punchers, cutting machines, separators), paper jogging machines, pencil sharpeners, staplers, typewriters
other information technology equipment	photoprinting equipment, public information terminals, multimedia equipment
postage equipment	mail processing machines, postage machines
telecommunication network infrastructure equipment	billing equipment, multiplexers, network powering equipment, network terminating equipment, radio basestations, repeaters, transmission equipment, telecommunication switching equipment
telecommunication terminal equipment	facsimile equipment, key telephone systems, modems, PABXs, pagers, telephone answering machines, telephone sets (wired and wireless)

NOTE 3 The requirements of IEC 60065 may also be used to meet safety requirements for multimedia equipment. See IEC Guide 112, *Guide on the safety of multimedia equipment*.

This list is not intended to be comprehensive, and equipment that is not listed is not necessarily excluded from the Scope.

Equipment complying with the relevant requirements in this standard is considered suitable for use with process control equipment, automatic test equipment and similar systems requiring information processing facilities. However, this standard does not include requirements for performance or functional characteristics of equipment.

1.1.2 Additional requirements

Requirements additional to those specified in this standard may be necessary for:

- equipment intended for operation in special environments (for example, extremes of temperature; excessive dust, moisture or vibration; flammable gases; and corrosive or explosive atmospheres);
- electromedical applications with physical connections to the patient;
- equipment intended to be used in vehicles, on board ships or aircraft, in tropical countries, or at altitudes greater than 2 000 m;
- equipment intended for use where ingress of water is possible; for guidance on such requirements and on relevant testing, see Annex T.

NOTE Attention is drawn to the fact that authorities of some countries impose additional requirements.

1.1.3 Exclusions

This standard does not apply to:

- power supply systems which are not an integral part of the equipment, such as motor-generator sets, battery backup systems and transformers;
- building installation wiring;
- devices requiring no electric power.

1.2 Definitions

For the purpose of this International Standard the following definitions apply. Where the terms "voltage" and "current" are used, they imply the r.m.s. values, unless otherwise specified.

Definitions in alphabetical order of nouns

AREA, OPERATOR ACCESS	1.2.7.1
AREA, SERVICE ACCESS	1.2.7.2
BODY	1.2.7.5
CABLE, INTERCONNECTING	1.2.11.6
CABLE DISTRIBUTION SYSTEM	1.2.13.14
CHEESECLOTH	1.2.13.15
CIRCUIT, ELV	1.2.8.7
CIRCUIT, LIMITED CURRENT	1.2.8.9
CIRCUIT, PRIMARY	1.2.8.4
CIRCUIT, SECONDARY	1.2.8.5
CIRCUIT, SELV	1.2.8.8
CIRCUIT, TNV	1.2.8.11
CIRCUIT, TNV-1	1.2.8.12
CIRCUIT, TNV-2	1.2.8.13
CIRCUIT, TNV-3	1.2.8.14
CLEARANCE	1.2.10.1
CONDUCTOR, PROTECTIVE BONDING	1.2.13.11
CONDUCTOR, PROTECTIVE EARTHING	1.2.13.10
CORD, DETACHABLE POWER SUPPLY	1.2.5.5
CORD, NON-DETACHABLE POWER SUPPLY	1.2.5.6
CREEPAGE DISTANCE	1.2.10.2
CURRENT, PROTECTIVE CONDUCTOR	1.2.13.13
CURRENT, RATED	1.2.1.3
CURRENT, TOUCH	1.2.13.12
CUT-OUT, THERMAL	1.2.11.3
CUT-OUT, THERMAL, AUTOMATIC RESET	1.2.11.4
CUT-OUT, THERMAL, MANUAL RESET	1.2.11.5
EARTHING, FUNCTIONAL	1.2.13.9
ENCLOSURE	1.2.6.1
ENCLOSURE, ELECTRICAL	1.2.6.4
ENCLOSURE, FIRE	1.2.6.2
ENCLOSURE, MECHANICAL	1.2.6.3
ENERGY LEVEL, HAZARDOUS	1.2.8.10
EQUIPMENT, CLASS I	1.2.4.1
EQUIPMENT, CLASS II	1.2.4.2
EQUIPMENT, CLASS III	1.2.4.3